



Quick Installation Guide

Mobile Wi-Fi

* Images are for demonstration only.

@2025 TP-Link 7106512051 REV1.0.1

Safety Information

- · Keep the device away from water, fire, humidity or hot environments.
- Do not attempt to disassemble, repair, or modify the device. If you need service, please contact us.
- Do not use the device where wireless devices are not allowed.
- This equipment can be powered only by equipments that comply with Power Source Class 2 (PS2) or Limited Power Source (LPS) defined in the standard of IEC 62368-1.

TP-Link hereby declares that the device is in compliance with the essential requirements and other relevant provisions of directives 2009/125/EC. 2014/53/EU. 2011/65/EU and (EU) 2015/863.

The original EU Declaration of Conformity may be found at https://www.tp-link.com/en/support/ce TP-Link hereby declares that the device is in compliance with the essential requirements and other relevant provisions of the Radio Equipment Regulations 2017.

The original UK Declaration of Conformity may be found at https://www.tp-link.com/support/ukca

CAUTION!

Avoid replacement of a battery with an incorrect type that can defeat a safeguard.

Avoid disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery,

Avoid disposal of a battery into fire or a hot oven, or mechanically crushing or cutting of a battery, that can result in an explosion.

Do not leave a battery in an extremely high temperature surrounding environment that can result in

an explosion or the leakage of flammable liquid or gas. Do not leave a battery subjected to extremely low air pressure that may result in an explosion or the leakage of flammable liquid or gas.

Risk of explosion if the battery is replaced by an incorrect type.

Screen Display

Home Screen

Press \equiv to enter the menu screen. Press \circlearrowleft to turn on or off the screen display.



Menu Screen

Press ≡ to switch between icons. Press ७ to select an icon.



The screen display will automatically turn off after being idle for a while. To turn it on again, press the ७ or ≡ button.

Charging Your Mobile Wi-Fi

Method 1

Via a Wall Outlet (Recommended)

Method 2

Via a Computer







- - The power adapter is not provided by TP-Link.

1. Install the SIM Card and Battery

- a. Remove the back cover.
- b. Install your SIM card.
- c. Install the provided battery.





• If you have a micro SD card, you can install it into the SD card slot for storage and media sharing.

2. Connect to the Internet

a. Power on the Mobile Wi-Fi.

Press and hold the Power button υ until the welcome screen appears.




b. Connect your smart device to the Mobile Wi-Fi. To view the SSID and password, press the

■ button to switch to the Device Info icon, then press the Power button υ to enter the screen.









- If you cannot access the internet, refer to FAQ > Q1.
 - By default, Power Saving is enabled and the Mobile Wi-Fi will turn off Wi-Fi when no wireless devices are connected to it for 10 minutes. To resume the Wi-Fi connection, press the ϕ or \equiv button. You can also go to the menu screen, web management page or tpMiFi App to disable Power Saving.

Managing Your Mobile Wi-Fi

Manage your Mobile Wi-Fi using any of the methods below. You can customize Wi-Fi settings, block Wi-Fi devices and more.

tpMiFi App

1. Get the tpMiFi app from App Store or Google Play, or by scanning the QR code.









- 2. Connect your wireless device to the Mobile Wi-Fi.
- 3. Launch the tpMiFi app and create a password to log in.

Web Management Page

- 1. Connect your wireless device to the Mobile Wi-Fi. If it is a computer, make sure it is set to obtain an IP address automatically.
- 2. Launch a web browser and visit http://tplinkmifi.net or http://192.168.0.1. Create a password to log in.





FAQ (Frequently Asked Questions)

Q1. What should I do if I cannot access the internet (one of the following messages appears on the home screen)?

A1. PIN Required

 Your SIM card is PIN protected. Log in to the web management page (http://tplinkmifi.net) on your phone, then enter the PIN provided by your mobile carrier.

A2. No SIM Card

Power off the Mobile Wi-Fi and reinstall your SIM card.

A3. No Service

- · Verify that your SIM card is an LTE or WCDMA SIM card.
- Verify that your SIM card is in your carrier's service area and has sufficient credit.
- Log in to the web management page (http://tplinkmifi.net) on your phone. Go to Dial-up to view parameters in Dial-up Settings section. and verify that the parameters (i.e. APN, username and password)

provided by your mobile carrier are correct. If they are not correct, enter the correct information or create a new profile, then save the settings.

A4. R icon

• Enter the Menu screen, go to Data Roaming, and turn on Data Roaming.

Q2. How do I restore the Mobile Wi-Fi to its factory default settings?

A. With the Mobile Wi-Fi powered on, remove the cover, then use a pin to press and hold the Reset button until "Power Off" appears on the screen. Note: Restoring the device to its factory defaults will clear all your settings.

